




Stealth Edge Pro 4G/LTE 5G

High Power Home & Building Cellular Signal Boosters

**6 BAND
MULTI BAND
Home & Office**



\$699.95

Installation Extra



HIGH POWER CELLULAR HOME & OFFICE BOOSTER SOLUTIONS

For use in Locations with Poor Indoor Cellular Signal

The Stealth Edge Pro boosters are designed to provide indoor coverage for Home & Office Locations that shield cellular signal. LED level indicators make installation quick, easy and effective. Automatic oscillation control, and network overload protection maintain maximum gain and coverage at all times. These boosters can be used with optional splitters and antennas to provide multiple area coverage.



Connects you in Fair signal Areas



Reduces Dropped Calls



Multiple Users Multiple Devices



LED Signal Gain Indicators



Increases data Speeds up to 30 times



Easy Install



The Booster captures the signal from outside and boosts it indoors
It takes the weak signal from your phone and boosts it back to the tower



Boosting Your

Cell Signal Anywhere

How much coverage area will I get?

First you should determine the signal strength outside the building. Then see the coverage area chart below to see how much area you can expect to cover. In locations where the outside signal is weak, you can expect the coverage area to be reduced.

NOTE: Stealth Edge Pro boosters are best suited for locations with poor indoor signal and fair outdoor signal

STEALTH EDGE PRO MODELS

PART NUMBER	BOOSTER CONNECTORS	INSIDE ANTENNA	ANTENNA CABLE	OUTSIDE ANTENNA	ANTENNA CABLE	XTRA CABLE
BBEPGP	F	PANEL	20FT RG6	PANEL	20FT RG6	30FT RG6
BBEPGTP	F	PANEL	20FT RG6	OMNI X-TUBE	20FT RG6	30FT RG6
BBEPGAP	F	PANEL	20FT RG8	ARROW DIRECTIONAL	20FT RG6	30FT RG6
BBEPNP	N	PANEL	20FT C205	PANEL	50FT LMR400	N/A
BBEPNTP	N	PANEL	20FT C205	OMNI X-TUBE	50FT LMR400	N/A
BBEPNAP	N	PANEL	20FT C205	ARROW DIRECTIONAL	50FT LMR400	N/A

NOTE: Stealth Edge Pro Maximum Gain:

Band 12/13/17/700MHz &, Band 5/850MHz 65dB * Band 2/25 1900Mhz & Band 4/2100MHz 72dB

STEALTH EDGE PRO COVERAGE AREA

OUTSIDE CELLULAR SIGNAL LEVEL	UP TO COVERAGE AREA SQFT.
5 Bars	5000
4 Bars	3500
3 Bars	2000
2 Bars	1000
1 Bar	Might not connect
0-1 Bar	Might not connect

Outside Antenna Types:



PANEL - SEMDP1:
Wide Directional High Gain Antenna
Provides 180 degree Radiation Pattern



ARROW DIRECTIONAL - SEMDA2:
Beam Directional High Gain Antenna
Provides 110 degree Radiation Pattern



OMNI X-TUBE - SEMDT1:
Omni Directional High Performance
Provides 360 degree Radiation Pattern

STEALTH EDGE PRO SERIES TECHNICAL DATA

FREQUENCIES	700 lower 700 upper 850 1900 1700/2100 MHz
MODEL	EDGE PRO SERIES
MODULATIONS	2G, 3G, 3G+, 4G, 4G+, 5G GSM, HSPA, CDMA, LTE, LTE A
TX POWER	1 watts Max EIRP
NOISE FIGURE	<4 dB
FLATNESS	+/- 3 dB
POWER SUPPLY	120V AC/DC
OPERATING TEMP	-30 C to +85 C
DIMENSIONS	L 4.72"xW 4.25"xH 1.25" (inch) L12xW10.8xH 3.2 (cm)
WEIGHT	1.5 lbs / 0.660 kg
CABLE	INCLUDED IN ALL KITS



Smoothtalker offers fully automatic gain and oscillation control also automatic power control which protects the Cellular Network. This makes Smoothtalker boosters totally network friendly and deliver the best signal to your cellular device at MAXIMUM power.



Voice2net Corp

Ontario Canada

1-844-713-1555

In 2001 Smoothtalker designed the first Digital Mobile Amplifier in North American with FCC and IC Approval. They continue to lead with the most powerful and intelligent cellular boosters in the world.